

Manual, Assembly instruction: Brodit 217230

Universal 2-slot USB-C desktop charging cradle. Fits devices with or without a protective case: width 55–90 mm, thickness 7–24 mm. Powered via USB-C (power supply not included, charging only, no data transfer). Equipped with hand-tightening locking wheels.

1.)



2.)



3.)



4.)



Please read these instructions carefully and review all illustrations before using the stand. It is important that all adjustments are made to fit the device being used. Always hold the supplied key by its short end.

1. USB-C Connector: Remove the recessed key from its storage compartment. Place the stand on its rear short side. Insert the long end of the key into the hole on the underside of the stand. Position device straight onto the USB-C connector. Hold the key firmly to prevent the connector from being pushed inward by the device. At the same time, press device into place until you feel it connect securely to the USB-C connector. Keep device in exactly the same position. Insert the long end of the key into the hole on the short side of the stand. Tighten the screw on the short side of the stand to lock the connector at the desired height. Tighten the screw until you feel increased resistance. Changing to a different device: Loosen the screws on the short side of the stand completely until they meet increased resistance. Loosen the locking wheels and move the supports to their outermost positions. Repeat Step 1 to adjust the stand for your new device.

2. Rear Support: Hold device in an upright position. Press the rear support against device. Secure the support in the desired position using the locking wheel.

3. Side Supports: Hold the device in an upright position. Press the side supports against the device. Secure the supports in the desired position using the locking wheels. Connect the power cable (not included).

4. Docking stand with two different devices installed.