

Manual, Assembly instruction: Brodit 759229

For fixed installation. With active MultiMoveClip. 12/24V. With tilt swivel. With Easy-switching system.

1.)



2.)



3.)



4.)



Please read all of the instructions and look at the pictures before installing.

1. To place the device in the sleeve: Place the device onto the backpart of the sleeve. Carefully connect the charging connector to the device. NOTE: It is very important to hold the connector straight in front of the device and connect it straight into the device (if you angle the connector/place it askew into the device, you risk to damage the connector/device). Place the front part/frame over the device and attach it by screwing the enclosed screws into place on the back side of the sleeve. Place the short screw in the position shown in the picture and the long screws into the other predrilled holes. The device is now securely in place and can not be removed without loosening the screws. **2.** To install the active MultiMoveClip: Loosen the screw in the center of the Power Block so you can remove the tilt swivel attaching plate on the back. Place the attaching plate onto the desired position and screw it into place with the enclosed screws. Place the Power Block over the attaching plate so the screw fits in the hole in the tilt swivel. Tighten the screw until the MultiMoveClip is firmly in place, but still can be adjusted. **3.** To place the sleeve onto the active MultiMoveClip: Place the sleeve above the Power Block and slide/press it straight downward into the Power Block so you hear/feel it snaps into place. The device is now connected to the charging. To remove the sleeve from the active MultiMoveClip: Press forward on the release arm on the Power Block so the sleeve is set free. Press/lift the sleeve straight upward, out from the Power Block. **4.** The product is in place.